
FDB 19 Heavy Duty Adjustable RCCB





ELECTRICAL PROTECTION FOR PROBLEM INSTALLATIONS

CONSTRUCTION SITES

MINES AND QUARRIES

STAGE AND FILM SETS

MOBILE PLANT AND CRANES A range of heavy duty electrical protection units designed to overcome inherent earth leakage or inrush currents. The unit combines a variable sensitivity and time delay RCD (see EFU10/15 Data Sheet) together with a triple pole MCCB (minimum 15KA) to provide overcurrent and short circuit protection.

The installation of this unit is recommended to achieve the optimum level of protection without the inconvenience of spurious tripping. Numerous applications throughout industry from construction sites, mines and quarries to the protection of stage lighting systems where thyristor spikes can trip conventional RCD's.

A standard feature of the FDB19 is its non-fail safe operation ideal for primary breaker installations or those that are unmanned or prone to supply interruption. A fail-safe version requiring reset of MCCB on restoration of a supply interruption is also available.

Housed in robust, lockable steel enclosures to IP65, this range complements our standard RCD range and overcomes the difficulty of protecting problem installations.



FDB 19 Heavy Duty Adjustable RCCB

Specification

Voltage:	380/440V 50Hz TP + N		
Ratings:	As Below		
RCD:	To BS4293 (Where applicable)		
Sensitivity:	Dip Switch Adjustable		
Low: High:	10mA to 640mA in 10mA Steps 100mA to 6.4A in 100mA Steps		
Time Delay:	Dip Switch Adjustable 50mS to 3.15 Secs in 100mS Steps		
MCCB:	3 Pole, Current limiting type: 15/35KA, BS4752		
Enclosure:	Zinc coated steel, hinged door. Gland plates top & bottom Protection IP65		
Finish:	Epoxy Powder – Mist grey (RAL 7032)		

As with all our products, we are happy to tailor our standard specification to suit individual applications.


Order Reference

Current Rating (amps)	Order Reference	Current Rating (amps)	Order Reference
15	19B15	125	19B125
30	19B30	150	19B150
60	19B60	200	19B200
80	19B80	300	19B300
100	19B100	400	19B400

To specify fail-safe RCD please add suffix/FS to order reference.







In line with our policy of constant improvements, we reserve the right to vary the specifications contained in this leaflet.

FDB Electrical Ltd Reynard Business Park Windmill Road Brentford Middlesex TW8 9NZ Tel: 020 8568 4621

We manufacture a complete range of electrical safety products.
Please contact us for

